

FAST ORTHOGONAL MATCHING PURSUIT FOR EXACT RECOVERY AND SPARSE APPROXIMATION

HUIYUAN YU , JIA HE , AND MAGGIE X. CHENG*

Abstract. Orthogonal Matching Pursuit (OMP) has been a powerful method in sparse signal recovery and approximation. However OMP suffers computational issue when the signal has large number of non-zeros. This paper advances OMP in two fronts: it offers a fast algorithm for the orthogonal projection of the input signal at each iteration, and a new selection criterion for making the greedy choice, which reduces the number of iterations it takes to recover the signal. The proposed modifications to OMP directly reduce the computational complexity. Experiment results show significant improvement over the classical OMP in computation time. The paper also provided a sufficient condition for exact recovery under the new greedy choice criterion. For general signals that may not have sparse representations, the paper provides a bound for the approximation error. The approximation error is at the same order as OMP but is obtained within fewer iterations and less time.

Key words. Greedy Algorithm, Compressive Sensing, Sparse Signal Recovery, Approximation, Orthogonal Matching Pursuit, Restricted Isometry Property

AMS subject classifications. 65F10, 65F20, 68Q25, 68R10, 68W25

1. Introduction. Let \mathbf{x} be a d -dimensional real signal. Suppose there is a real measurement matrix $\Phi \in \mathbb{R}^{N \times d}$, through which we can obtain an N -dimensional measurement $\mathbf{y} = \Phi \mathbf{x}$. Usually $N < d$, which presents an underdetermined system. How to reconstruct the original signal \mathbf{x} from an underdetermined system? If \mathbf{x} is sparse, then by exploiting sparsity, we may be able to find a unique solution. \mathbf{x} is called a k -sparse signal if \mathbf{x} has at most k non-zero components.

The measurement matrix Φ is also called a dictionary, and each column φ of the dictionary called an atom. Let $\mathcal{J} = \{1, \dots, d\}$ represent the index set of all atoms in the dictionary. If the dictionary is overcomplete, there are many representations of $\mathbf{y} = \sum_{\gamma \in \mathcal{J}} a_{\gamma} \varphi_{\gamma}$. Intuitively, we would like to find the sparsest solution: $\min_{\mathbf{x}} \|\mathbf{x}\|_0$ subject to $\mathbf{y} = \Phi \mathbf{x}$, but it is an NP-hard problem. Different optimization

*Department of Applied Mathematics, College of Computing, Illinois Institute of Technology, Chicago, IL, 60616. (maggie.cheng@iit.edu).

principles lead to different sparse representations of \mathbf{y} , for example, basis pursuit (BP) [12, 7, 6] and the method of frames (MOF) [9] among many others [14, 23]:

- Find a representation of the input signal whose coefficients have the minimal ℓ_1 norm.

$$\text{(BP)} \quad \min_{\mathbf{x}} \|\mathbf{x}\|_1 \quad \text{subject to } \mathbf{y} = \Phi \mathbf{x}$$

- Find a representation of the input signal whose coefficients have the minimal ℓ_2 norm.

$$\text{(MOF)} \quad \min_{\mathbf{x}} \|\mathbf{x}\|_2 \quad \text{subject to } \mathbf{y} = \Phi \mathbf{x}$$

BP and MOF both provide convex relaxation to the ℓ_0 norm minimization problem, however, neither of them provides the sparsest solution, except those satisfying the sparsity condition specified in [11].

Matching Pursuit (MP) [16] uses an iterative procedure that directly addresses the sparsity issue. Orthogonal Matching Pursuit (OMP) [19, 21, 22] inherits the greedy approach from MP that selects an atom with the maximal correlation with the residual at present, but improves over the standard MP by adding least square minimization at each iteration. Let Γ be the index set of atoms found so far, the least square estimation is used for computing the orthogonal projection of the input signal \mathbf{y} onto the subspace spanned by the atoms indexed by Γ :

$$\text{(OMP)} \quad \min_{\mathbf{x}_\Gamma} \|\mathbf{y} - \Phi_\Gamma \mathbf{x}_\Gamma\|_2^2 \quad \text{with } |\Gamma| \leq k$$

The complete OMP algorithm is included in the Appendix for comparison purpose.

OMP has been shown to have better results than MP. Many variations of OMP have been developed [13, 15, 8, 18, 17]. Under certain conditions OMP provides recovery guarantee [4, 22, 21, 10, 3, 5]. The excellent performance of OMP results from the orthogonal projection of \mathbf{y} onto the subspace spanned by the atoms selected

so far. The least square solution is obtained by $\mathbf{x}_\Gamma = \Phi_\Gamma^+ \mathbf{y}$. As Γ increases, solving the least square problem significantly increases the computational load. In this paper, we propose two fundamental improvements over classical OMP to avoid the high complexity of computing pseudo inverse over an increasing-sized matrix:

- When solving the least square problem at each iteration, instead of computing $\Phi_\Gamma^+ \mathbf{y}$ over the entire support Γ , it uses successive regression over a single atom. It makes the same greedy choice as OMP does at each iteration, but is much faster due to reduced computation load. The proposed algorithm is called OMP-SR.
- Selecting a block of atoms instead of one atom at each iteration. An important invariant held by the classical OMP is that only one optimal atom can be selected in each iteration so that under certain condition OMP finds k non-zeros in k iterations. Without this invariant, the sufficient condition may not lead to exact recovery. The blocked version will extend the greedy choice to multiple atoms at each iteration but still preserve the convergence property of OMP. The proposed algorithm is called blocked successive regression (BSR).

In general, the measurement \mathbf{y} is often with noise. A general signal may be represented as the linear combination of atoms from the dictionary with additive noise,

$$\mathbf{y} = \Phi \mathbf{x} + \boldsymbol{\varepsilon}.$$

We are interested in the best approximation of \mathbf{y} using a linear combination of atoms. *Best approximation* is the one with the smallest approximation error measured by the ℓ_2 norm of the residual, and hence, the optimization principle is,

$$\text{(Sparse Approximation)} \quad \min_{\mathbf{x}} \|\mathbf{y} - \Phi \mathbf{x}\|_2 \quad \text{subject to } \|\mathbf{x}\|_0 \leq k$$

1.1. Major Results.

- Improvement on OMP, which preserved the excellent stability and performance guarantee of OMP but are more computationally efficient and hence

much faster.

- Theories of sufficient conditions for both exact recovery and sparse approximation. These sufficient conditions are specified in terms of the properties of the dictionary. Compared to the popular Restricted Isometry Property (RIP), these conditions are more computationally feasible to check [20, 2, 1].
- Approximation error of BSR for general signals. The error bound extends the result of [21] to the blocked version and is shown to be at the same order as OMP, but is obtained with fewer number of iterations. Table 3 shows the approximation error, iterations, and running time.

1.2. Notation.

- Φ^\top : transpose of matrix Φ
- Φ^+ : pseudo inverse of matrix Φ
- $(\Phi^\top \Phi)^{-1}$: inverse of matrix $(\Phi^\top \Phi)$
- $\|A\|_{p \rightarrow q} = \sup_{\mathbf{x} \neq 0} \frac{\|A\mathbf{x}\|_q}{\|\mathbf{x}\|_p}$: operator norm of matrix A .
- $\|A\|_{p \rightarrow p}$ is abbreviated to $\|A\|_p$.

2. Orthogonal Matching Pursuit through Successive Regression (OMP-SR)

OMP-SR is a fast implementation of OMP. When solving the least square problem at each iteration of OMP, it avoids the expensive computation for the pseudo inverse of $\Phi_{J_{t-1}}$; instead, it only projects onto the atom selected in the current iteration via univariate regression, and then updates the coefficients of atoms selected in previous iterations through a backtracking procedure: $b_l = \beta_l - \sum_{k=l+1}^t b_k \gamma_{l,k}$ (see Algorithm 2.1), where $\beta_t = \frac{\langle \mathbf{z}_t, \mathbf{y} \rangle}{\langle \mathbf{z}_t, \mathbf{z}_t \rangle}$ is the coefficient newly obtained in the current iteration, b_l is the updated coefficient for the atoms selected in previous iterations. Note that the inner product $\langle \mathbf{z}_l, \mathbf{z}_l \rangle$ does not need to be recomputed. It only needs to be computed once, that is when we compute β_l in the l -th iteration.

OMP-SR selects the same atom and generates the same residual as OMP does at each iteration, and therefore returns the same result as OMP. OMP-SR starts to show performance gain over OMP when the number of non-zeros in \mathbf{x} increases due to not having to compute the pseudo inverse of a growing matrix.

Algorithm 2.1 OMP-SR

Initialization: $\mathbf{a}_0 = \mathbf{z}_0 = \mathbf{1}$, $\mathbf{r}^0 = \mathbf{y}$, $J^0 = \emptyset$

for $t = 1$ **to** κ **do**

Choose $j^t = \arg \max_{j \in \mathcal{J} \setminus J^{t-1}} \left| \sum_{i=1}^N \Phi_{i,j} \mathbf{r}_i^{t-1} \right|$

Let \mathbf{a}_t be the j^t -th column of matrix Φ .

Regress \mathbf{a}_t on \mathbf{z}_l and get coefficients

$$\gamma_{l,t} = \frac{\langle \mathbf{z}_l, \mathbf{a}_t \rangle}{\langle \mathbf{z}_l, \mathbf{z}_l \rangle}, \quad \text{for } l = 0, \dots, t-1$$

Compute $\mathbf{z}_t = \mathbf{a}_t - \sum_{l=0}^{t-1} \gamma_{l,t} \mathbf{z}_l$

Regress \mathbf{y} on \mathbf{z}_t to get $\beta_t = \frac{\langle \mathbf{z}_t, \mathbf{y} \rangle}{\langle \mathbf{z}_t, \mathbf{z}_t \rangle}$

Let $b_t = \beta_t$

if $t > 1$ **then**

for $l = t-1$ **to** 1 **do**

$$b_l = \beta_l - \sum_{k=l+1}^t b_k \gamma_{l,k}$$

end for

end if

Update index set $J^t = J^{t-1} \cup \{j^t\}$

Update residual $\mathbf{r}^t = \mathbf{y} - \sum_{l=1}^t b_l \Phi_{j^l}$

end for

Let $\mathbf{x}_{j^t} = b_t$ for $t = 1, \dots, \kappa$, and let $\mathbf{x}_j = 0$ for $j \notin J^\kappa$

Return \mathbf{x}

3. Blocked Successive Regression (BSR). BSR builds on the idea of successive regression in OMP-SR but selects a block of atoms at each iteration. The block size c is a hyper parameter, usually decided by a grid search. The algorithm is still greedy in nature: in each iteration it selects the atoms that have the largest correlations with the residual measured by the ℓ_2 norm. Each iteration of BSR performs an orthogonal projection of \mathbf{y} over c newly selected atoms, instead of over $|\Gamma|$ atoms, which could be costly as $|\Gamma|$ increases with iterations. Subsequently the coefficients for atoms selected in previous iterations are updated through $b_i = \beta_i - \sum_{k=l+1}^t \sum_{j \in \Gamma_k} b_j \gamma_{i,j}$ (see Algorithm 3.1).

Making the greedy choice $\Gamma_t = \arg \max_{\substack{|\Omega|=c \\ \Omega \subset \mathcal{J} \setminus \Gamma}} \|\Phi_\Omega^\top \mathbf{r}^{t-1}\|_2$ does not incur combinatorial complexity. In fact, it only needs to compute the absolute inner product values $|\langle \varphi_j, \mathbf{r}^{t-1} \rangle|$ for $\varphi_j \in \Phi \setminus \Phi_\Gamma$ and take the largest c columns.

Algorithm 3.1 BSR

Initialization: $\mathbf{r}^0 = \mathbf{y}$, $\Gamma = \phi$, $\mathbf{z}_0 = \mathbf{1}$

for $t = 1$ **to** κ **do**

$\Gamma_t = \arg \max_{\substack{|\Omega|=c \\ \Omega \subset \mathcal{J} \setminus \Gamma}} \|\Phi_\Omega^\top \mathbf{r}^{t-1}\|_2$

for each $j \in \Gamma_t$ **do**

Let \mathbf{a}_j be the j -th column of matrix Φ .

Regress \mathbf{a}_j on \mathbf{z}_0 to get coefficient $\gamma_{0,j} = \frac{\langle \mathbf{z}_0, \mathbf{a}_j \rangle}{\langle \mathbf{z}_0, \mathbf{z}_0 \rangle}$

Compute $\mathbf{z}_j = \mathbf{a}_j - \gamma_{0,j} \mathbf{z}_0$

if $t > 1$ **then**

Regress \mathbf{a}_j on Z_{Γ_t} to get coefficients

$\gamma_{\Gamma_t, j} = Z_{\Gamma_t}^+ \mathbf{a}_j$, for $l = 1, \dots, t-1$

Compute $\mathbf{z}_j = \mathbf{z}_j - \sum_{l=1}^{t-1} \sum_{i \in \Gamma_l} \gamma_{i,j} \mathbf{z}_i$

end if

end for

Regress \mathbf{y} on Z_{Γ_t} to get coefficients $\beta_{\Gamma_t} = Z_{\Gamma_t}^+ \mathbf{y}$

Let $\mathbf{b}_{\Gamma_t} = \beta_{\Gamma_t}$

if $t > 1$ **then**

for $l = t-1$ **to** 1 **do**

for $i \in \Gamma_l$ **do**

$b_i = \beta_i - \sum_{k=l+1}^t \sum_{j \in \Gamma_k} b_j \gamma_{i,j}$

end for

end for

end if

Update index set $\Gamma = \Gamma \cup \Gamma_t$

Update residual $\mathbf{r}^t = \mathbf{y} - \Phi_\Gamma \mathbf{b}_\Gamma$

Break if $\|\mathbf{r}^t\|_2 \leq \delta$

end for

Let $\mathbf{x}_\Gamma = \mathbf{b}_\Gamma$, and let $\mathbf{x}_{\mathcal{J} \setminus \Gamma} = 0$

Return \mathbf{x}

The BSR algorithm halts if the residual becomes too small or it has exhausted κ iterations, which amounts to two of the three halting rules listed in [17] for matching pursuit type of algorithms.

4. Conditions for Exact Recovery.

4.1. Background. Assume there are k non-zero entries in a d -dimensional signal \mathbf{x} , and $k \ll d$. Let $\Lambda_{\text{opt}} = \{i_1, \dots, i_k\}$ be the set of indices for the non-zero entries of \mathbf{x} . Without loss of generality, we can partition the measurement matrix as $\Phi = [\Phi_{\text{opt}} | \Psi]$

so that Φ_{opt} has k columns, $\Phi_{\text{opt}} = [\varphi_{i_1}, \dots, \varphi_{i_k}]$, and Ψ has the remaining $d - k$ columns.

In the absence of noise, the measured signal \mathbf{y} has a sparse representation: $\mathbf{y} = \Phi \mathbf{x} = \sum_{j \in \Lambda_{\text{opt}}} a_j \varphi_j$. Exact recovery aims to recover the coefficients a_j for all atoms indexed by Λ_{opt} , which are the non-zero entries in \mathbf{x} .

4.1.1. The Exact Recovery Condition of OMP. In [21], the exact recovery condition for OMP is established. Under this condition, OMP can find all optimal atoms. Let \mathbf{r} be the residual at the current iteration. Initially before the first iteration, \mathbf{r} is set to be $\mathbf{r} = \mathbf{y}$.

To see how the OMP algorithm locates the columns of Φ_{opt} , we define the greedy choice ratio as follows:

$$(4.1) \quad \rho(\mathbf{r}) \stackrel{\text{def}}{=} \frac{\|\Psi^\top \mathbf{r}\|_\infty}{\|\Phi_{\text{opt}}^\top \mathbf{r}\|_\infty} = \frac{\max_{\psi} |\langle \psi, \mathbf{r} \rangle|}{\|\Phi_{\text{opt}}^\top \mathbf{r}\|_\infty},$$

where ψ ranges over columns of Ψ .

A sufficient condition for OMP algorithm to succeed is that $\rho(\mathbf{r}) < 1$ holds for all iterations. When $\rho(\mathbf{r}) < 1$ holds, the greedy algorithm will pick a column from Φ_{opt} that has not been selected by the algorithm. The columns that have been selected so far will not be the column that gives the maximum absolute inner product $\|\Phi_{\text{opt}}^\top \mathbf{r}\|_\infty$, because the residual \mathbf{r} is orthogonal to them. Each iteration of OMP will select one new optimal column, so the OMP algorithm is guaranteed to locate k optimal columns in k iterations.

If the ratio fails to hold, e.g., if $\rho(\mathbf{r}) = 1$, the algorithm is not guaranteed to make the correct choice, since the absolute inner product of the residual with a non-optimal column is the same as the absolute inner product with an optimal column and there is no reason to prefer one over another. A non-optimal column could be selected in

this case. If $\rho(\mathbf{r}) > 1$, the algorithm will certainly select a non-optimal column. In summary, if $\rho(\mathbf{r}) < 1$ fails to hold at any iteration, the algorithm could fail to locate k optimal columns in k iterations.

4.1.2. The Exact Recovery Condition of OMP-SR. Algorithm OMP-SR essentially is an OMP algorithm with fast implementation: it starts with the same initial residual \mathbf{r}^0 and selects the same atom in the next iteration, so the residual \mathbf{r}^t after the t -th iteration is the same. Since \mathbf{r}^t is used as input to the next iteration when choosing a column, the next iteration will result in the same residual \mathbf{r}^{t+1} . By induction, after k iterations the algorithm returns the same result as OMP does. The exact recovery condition for OMP-SR is the same as for OMP.

4.2. The Exact Recovery Conditions of BSR. BSR is essentially a greedy algorithm, which makes a greedy choice at each iteration, except that BSR selects a block of columns at each iteration with a fixed block size c ($c \geq 1$). If $c = 1$, BSR reduces to OMP-SR. We have learned that under the condition of $\rho(\mathbf{r}) < 1$, OMP and OMP-SR can find one optimal column in each iteration. Then for BSR, under what condition will each iteration of BSR only select the optimal columns from Φ_{opt} except the last iteration? This is the best case, in which BSR can locate all optimal columns within $\lceil k/c \rceil$ iterations. We call the condition for the best case as *the strong exact recovery condition for BSR*.

4.2.1. A Strong Exact Recovery Condition for BSR. Recall that $\Phi = [\Phi_{\text{opt}} | \Psi]$ so that Φ_{opt} has the k optimal columns, and Ψ has the remaining $d - k$ columns. Let \mathbf{r} denote the residual at the current iteration before the greedy choice is made.

For a fixed block size c , the greedy choice ratio is defined as follows:

$$(4.2) \quad \rho_c(\mathbf{r}) \stackrel{\text{def}}{=} \frac{\max_{\Omega_1} \|\Phi_{\Omega_1}^\top \mathbf{r}\|_2}{\max_{\Omega_2} \|\Phi_{\Omega_2}^\top \mathbf{r}\|_2},$$

such that $|\Omega_1| = |\Omega_2| = c$ and $|\Omega_2 \cap \Lambda_{\text{opt}}| > |\Omega_1 \cap \Lambda_{\text{opt}}|$, i.e., Ω_2 has at least one more optimal column than Ω_1 . Given a k -sparse signal, BSR can recover the signal within $\lceil k/c \rceil$ iterations if the following condition holds.

THEOREM 4.1 (The strong exact recovery condition for BSR). *A sufficient condition for BSR to recover a k -sparse signal within $\lceil k/c \rceil$ iterations is that*

$$(4.3) \quad \rho_c(\mathbf{r}) < 1$$

holds for all iterations.

Proof: In all but the last iteration, BSR algorithm will select c columns from Φ_{opt} that have not been selected by the algorithm. This can be observed from two aspects: 1) the columns that have been selected so far will not contribute to the maximum ℓ_2 -norm $\max_{\Omega_2} \|\Phi_{\Omega_2}^\top \mathbf{r}\|_2$ since the residual \mathbf{r} is orthogonal to them, therefore the maximum value have to be achieved by the new columns the algorithm has not seen so far; and 2) with $\rho_c(\mathbf{r}) < 1$, the BSR algorithm will select as many optimal columns as possible in each iteration. Therefore the c columns selected by the algorithm in each iteration (except the last) will not include any column from Ψ , and they all have to come from Φ_{opt} . In the last iteration it is possible to select non-optimal columns from Ψ because all optimal columns in Φ_{opt} have been exhausted. Therefore the BSR algorithm is guaranteed to locate k optimal columns in $\lceil k/c \rceil$ iterations. \square

4.2.2. A Weak Exact Recovery Condition for BSR. What is the condition for $\rho_c(\mathbf{r}) < 1$ to hold in Theorem 4.1? In the absence of a straightforward answer, we first discuss the condition for BSR to recover a k -sparse signal within k iterations, then revisit the condition (4.3).

We call the condition for BSR to recover a k -sparse signal within k iterations *the weak exact recovery condition for BSR*. For the weak condition, we use the same greedy choice ratio as defined in section 4.1.1: $\rho(\mathbf{r}) = \frac{\|\Psi^\top \mathbf{r}\|_\infty}{\|\Phi_{\text{opt}}^\top \mathbf{r}\|_\infty}$.

THEOREM 4.2 (The Weak Exact Recovery Condition for BSR). *A sufficient con-*

dition for BSR to recover a k -sparse signal within k iterations is that

$$(4.4) \quad \rho(\mathbf{r}) < 1$$

holds for all iterations.

Proof: If $\rho(\mathbf{r}) < 1$ holds, then in each iteration BSR can choose at least one optimal column from Φ_{opt} . This is because the BSR algorithm chooses the c columns that give the maximum ℓ_2 -norm $\max_{|\Omega|=c} \|(\Phi_{\text{opt}})_{\Omega}^{\top} \mathbf{r}\|_2$. The c columns that achieved the maximum ℓ_2 -norm have the largest c absolute inner products with residual \mathbf{r} , which certainly include the largest value. If the condition $\rho(\mathbf{r}) < 1$ holds in all iterations, the BSR algorithm is guaranteed to select at least one new column from Φ_{opt} . Therefore, for a k -sparse signal, BSR can find all optimal columns in at most k iterations. \square

Although intuitive, the condition in (4.4) expressed in terms of the greedy choice ratio cannot be checked before we know the residuals in all iterations. We need to establish a sufficient condition for the exact recovery by BSR in terms of the property of the dictionary Φ .

BSR will select at least one optimal column at each iteration but can also possibly select some non-optimal columns. We can split the columns of Ψ into two parts: $\Psi = [\Psi_J | \Psi_{\mathcal{J}}]$, where Ψ_J are the non-optimal columns that have been selected by BSR algorithm so far, and $\Psi_{\mathcal{J}}$ include the remaining columns.

Let matrix X be the submatrix of Φ that includes all columns of Φ_{opt} and the columns in Ψ that have been selected by BSR at the previous iterations, i.e., $X = [\Phi_{\text{opt}} | \Psi_J]$.

We first prove a lemma that can lead to the sufficient condition $\rho(\mathbf{r}) < 1$.

Let Π denote the index set for the columns in Φ_{opt} that have not been selected by the algorithm so far, so $|\Pi| \leq k$. Let $(\cdot)_{\Pi}$ denote the columns in the matrix indexed by Π , and $(\cdot)_{\Pi, \cdot}$ denotes the rows of the matrix indexed by Π .

LEMMA 4.3. *If $\max_{\boldsymbol{\psi}} \left\| (X^+)_{\Pi, \cdot} \boldsymbol{\psi} \right\|_1 < 1$, where vector $\boldsymbol{\psi}$ ranges over columns of $\Psi_{\mathcal{J}}$, then the residual \mathbf{r} satisfies $\rho(\mathbf{r}) < 1$.*

Proof:

$$\begin{aligned}
\rho(\mathbf{r}) &= \frac{\|\Psi^\top \mathbf{r}\|_\infty}{\|\Phi_{\text{opt}}^\top \mathbf{r}\|_\infty} \\
&\stackrel{(a)}{=} \frac{\|\Psi_{\mathcal{J}}^\top \mathbf{r}\|_\infty}{\|\Phi_{\text{opt}}^\top \mathbf{r}\|_\infty} \\
&\stackrel{(b)}{=} \frac{\|\Psi_{\mathcal{J}}^\top X (X^\top X)^{-1} X^\top \mathbf{r}\|_\infty}{\|\Phi_{\text{opt}}^\top \mathbf{r}\|_\infty} \\
&\stackrel{(c)}{=} \frac{\|\Psi_{\mathcal{J}}^\top (X (X^\top X)^{-1})_{\Pi} X_{\Pi}^\top \mathbf{r}\|_\infty}{\|\Phi_{\Pi}^\top \mathbf{r}\|_\infty} \\
&\stackrel{(d)}{\leq} \left\| \Psi_{\mathcal{J}}^\top \left((X^+)^\top \right)_{\Pi} \right\|_\infty \\
&\stackrel{(e)}{=} \left\| (X^+)_{\Pi, \cdot} \Psi_{\mathcal{J}} \right\|_1 \\
&\stackrel{(f)}{=} \max_{\boldsymbol{\psi}} \left\| (X^+)_{\Pi, \cdot} \boldsymbol{\psi} \right\|_1,
\end{aligned}$$

where $\boldsymbol{\psi}$ ranges over columns of $\Psi_{\mathcal{J}}$.

(a) is because $\|\Psi^\top \mathbf{r}\|_\infty = \|\Psi_{\mathcal{J}}^\top \mathbf{r}\|_\infty$, since columns in $\Psi_{\mathcal{J}}$ are orthogonal to \mathbf{r} .

(b) is due to that residual \mathbf{r} lies in the column span of X . Sparse representation of $\mathbf{y} = \sum_{j \in \Lambda_{\text{opt}}} a_j \boldsymbol{\varphi}_j$, so \mathbf{y} lies in the column span of Φ_{opt} . Since X includes all columns of Φ_{opt} , \mathbf{y} also lies in the column span of X . On the other hand, X includes all the columns found by the algorithm so far, so $\Phi_{\Gamma} \mathbf{s}_{\Gamma}$ also lies in the column span of X . Therefore the residual $\mathbf{r} = \mathbf{y} - \Phi_{\Gamma} \mathbf{s}_{\Gamma}$ also lies in the column span of X .

$X(X^\top X)^{-1} X^\top$ is a projector onto the column span of X . Since \mathbf{r} lies in the column span of X , so the projection of \mathbf{r} onto the column span of X is \mathbf{r} itself:

$$X(X^\top X)^{-1} X^\top \mathbf{r} = \mathbf{r}.$$

In the vectors $X^\top \mathbf{r}$ and $\Phi_{\text{opt}}^\top \mathbf{r}$, all the nonzero elements are from $\Phi_{\Pi}^\top \mathbf{r}$. Thus,

$$\|X^\top \mathbf{r}\|_\infty = \|\Phi_{\text{opt}}^\top \mathbf{r}\|_\infty = \|X_{\Pi}^\top \mathbf{r}\|_\infty = \|\Phi_{\Pi}^\top \mathbf{r}\|_\infty.$$

This leads to (c).

(d) is direct from the definition of matrix norm. Suppose that A is a matrix, and

\mathbf{v} is a vector with nonzero components. For $1 \leq p \leq \infty$, we have

$$\|A\|_p = \sup_{\mathbf{v} \neq 0} \frac{\|A\mathbf{v}\|_p}{\|\mathbf{v}\|_p}.$$

Therefore,

$$(4.5) \quad \|A\mathbf{v}\|_p \leq \|A\|_p \|\mathbf{v}\|_p.$$

(e) is due to that the matrix norm $\|\cdot\|_\infty$ takes the maximum absolute row sum, and $\|\cdot\|_1$ takes the maximum absolute column sum, so $\|A^\top\|_\infty = \|A\|_1$ for a given matrix A .

(f) follows the definition of matrix norm $\|\cdot\|_1$ to get the maximum absolute column sum of the matrix.

Therefore, if $\max_{\boldsymbol{\psi}} \left\| (X^+)_{\Pi, \cdot} \boldsymbol{\psi} \right\|_1 < 1$, where $\boldsymbol{\psi}$ ranges over columns of $\Psi_{\mathcal{J}}$, then $\rho(\mathbf{r}) < 1$. \square

Although condition $\max_{\boldsymbol{\psi} \in \Psi_{\mathcal{J}}} \left\| (X^+)_{\Pi, \cdot} \boldsymbol{\psi} \right\|_1 < 1$ is expressed in terms of the property of the dictionary, this condition still cannot be checked without executing the algorithm. In practice it is unlikely that the optimal columns are known *a priori*, so the submatrices $X, \Psi_{\mathcal{J}}$ cannot be located before the execution of the algorithm. More practical methods are needed to check the sufficient condition without the execution of the algorithm.

In [21], a fundamental property of the dictionary Φ , called *coherence* is defined as:

$$(4.6) \quad \mu \stackrel{\text{def}}{=} \max_{j \neq k} |\langle \boldsymbol{\varphi}_j, \boldsymbol{\varphi}_k \rangle|$$

Coherence μ is the maximum absolute value of pairwise inner product between the columns of the dictionary.

For a positive integer m , the cumulative coherence function, $\mu_1(m)$ of the dictio-

nary, is defined as

$$(4.7) \quad \mu_1(m) \stackrel{\text{def}}{=} \max_{|\Lambda|=m} \max_{\psi} \sum_{j \in \Lambda} |\langle \varphi_j, \psi \rangle|$$

where Λ is the set of indices for any m columns of Φ , and ψ ranges over the columns of Φ not indexed by Λ . $\mu_1(m)$ is the maximum cumulative coherence from any m columns of Φ .

Next we use the cumulative coherence property of the dictionary to derive a sufficient condition.

LEMMA 4.4. $\max_{\psi \in \Psi_{\mathcal{J}}} \|(X^+)_{\Pi, \cdot} \psi\|_1 < 1$ whenever $\mu_1(l) + \mu_1(n) < 1$ holds, where n is the number of columns in X , and $l = \min(|\Pi|, k - 1)$.

Proof:

$$\begin{aligned} & \max_{\psi \in \Psi_{\mathcal{J}}} \|(X^+)_{\Pi, \cdot} \psi\|_1 \\ &= \max_{\psi \in \Psi_{\mathcal{J}}} \left\| \left((X^\top X)^{-1} X^\top \right)_{\Pi, \cdot} \psi \right\|_1 \\ &= \max_{\psi \in \Psi_{\mathcal{J}}} \left\| \left((X^\top X)^{-1} \right)_{\Pi, \cdot} X^\top \psi \right\|_1 \\ &\leq \left\| \left((X^\top X)^{-1} \right)_{\Pi, \cdot} \right\|_1 \cdot \left(\max_{\psi \in \Psi_{\mathcal{J}}} \|X^\top \psi\|_1 \right) \\ &\leq \frac{\mu_1(n)}{1 - \mu_1(l)}, \end{aligned}$$

where n is the number of columns in X , and $l = \min(|\Pi|, k - 1)$.

It can be shown that

$$1). \quad \max_{\psi \in \Psi_{\mathcal{J}}} \|X^\top \psi\|_1 \leq \mu_1(n), \text{ and}$$

$$2). \quad \left\| \left((X^\top X)^{-1} \right)_{\Pi, \cdot} \right\|_1 \leq \frac{1}{1 - \mu_1(l)}.$$

1) can be proved following the definition of $\mu_1(\cdot)$,

$$\begin{aligned} \max_{\psi \in \Psi_{\mathcal{J}}} \|X^\top \psi\|_1 &= \max_{\psi \in \Psi_{\mathcal{J}}} \sum_{\varphi_j \in X} |\langle \varphi_j, \psi \rangle| \\ &\leq \mu_1(n). \end{aligned}$$

To prove 2), recall that the columns in the dictionary Φ are normalized unit

vectors (i.e., $\|\varphi\|_2 = 1$, for $\varphi \in \Phi$). We can represent

$$X^\top X = I_n + A,$$

where I_n is an identity matrix of size $n \times n$, and A is a matrix of size $n \times n$ collecting the pairwise inner products, so $A_{jk} = \langle \varphi_j, \varphi_k \rangle$, for $j \neq k$, and the diagonal $A_{jj} = 0$, and hence $\|A\|_1 \leq \mu_1(n-1)$ following the definition of the cumulative coherence function $\mu_1(\cdot)$.

When $\|A\|_1 < 1$, the Neumann series $\sum_{k=0}^{\infty} (-A)^k = (I_n + A)^{-1}$ (add reference here). Therefore, $(X^\top X)^{-1} = (I_n + A)^{-1} = \sum_{k=0}^{\infty} (-A)^k$. Note that having $\mu_1(n-1) < 1$ is sufficient to make $\|A\|_1 < 1$.

$$\begin{aligned} \left\| \left((X^\top X)^{-1} \right)_{\Pi, \cdot} \right\|_1 &= \left\| \left(\sum_{k=0}^{\infty} (-A)^k \right)_{\Pi, \cdot} \right\|_1 \\ &\stackrel{(a)}{\leq} \sum_{k=0}^{\infty} \|A_{\Pi, \cdot}\|_1^k \\ &\stackrel{(b)}{=} \frac{1}{1 - \|A_{\Pi, \cdot}\|_1} \\ &\stackrel{(c)}{\leq} \frac{1}{1 - \mu_1(l)}. \end{aligned}$$

(a) is due to $\|(-A)^k\|_1 \leq \|A\|_1^k$; (b) is due to $\|A_{\Pi, \cdot}\|_1 \leq \|A\|_1 < 1$; (c) is due to $\|A_{\Pi, \cdot}\|_1 \leq \mu_1(l)$. At the beginning before the first iteration, $X = \Phi_{\text{opt}}$, $\Pi = \Lambda_{\text{opt}}$, and A is a $k \times k$ matrix with zeros at the diagonal positions, so $\|A_{\Pi, \cdot}\|_1 \leq \mu_1(k-1)$. After the first iteration, $|\Pi| \leq k-1$. Therefore, $\|A_{\Pi, \cdot}\|_1 \leq \mu_1(l)$ for all iterations, with $l = \min(|\Pi|, k-1)$.

Therefore $\max_{\psi \in \Psi_{\mathcal{J}}} \left\| (X^+)_{\Pi, \cdot} \psi \right\|_1 < 1$ whenever $\mu_1(l) + \mu_1(n) < 1$. \square

Lemma 4.4 and Lemma 4.3 together lead to the following conclusion: the residual \mathbf{r} satisfies $\rho(\mathbf{r}) < 1$ whenever

$$(4.8) \quad \mu_1(l) + \mu_1(n) < 1.$$

4.2.3. Revisit Theorem 4.1: the Sufficient Condition for $\rho_c(\mathbf{r}) < 1$. Now we are ready to show that $\mu_1(l) + \mu_1(n) < 1$ is also sufficient for $\rho_c(\mathbf{r}) < 1$ to hold in Theorem 4.1.

Proof:

From the definition of $\rho_c(\mathbf{r})$, it is suggested that Ω_1 and Ω_2 both can have columns from Ψ and Φ_{opt} . If there is a column φ_j from Φ_{Ω_1} and a column φ_l from Φ_{Ω_2} such that $|\langle \varphi_j, \mathbf{r} \rangle| > |\langle \varphi_l, \mathbf{r} \rangle|$, then the greedy algorithm would have selected φ_j . In this case, we would switch the memberships of two columns in Ω_1 and Ω_2 as long as such switching does not violate the condition $|\Omega_2 \cap \Lambda_{\text{opt}}| > |\Omega_1 \cap \Lambda_{\text{opt}}|$. The only case that the switching is forbidden is that φ_j is a column in Ψ and φ_l is a column in Φ_{opt} so that switching would have violated the above condition. There will be at least one such column in Ψ and one column in Φ_{opt} that cannot be switched.

Let $\Theta_1 \subseteq \Omega_1$ and $\Theta_2 \subseteq \Omega_2$ be the indices for such non-switchable columns in Ψ and Φ_{opt} , respectively. We have $|\Theta_1| = |\Theta_2| = |\Omega_2 \cap \Lambda_{\text{opt}}| - |\Omega_1 \cap \Lambda_{\text{opt}}| \geq 1$. We define

$$(4.9) \quad \rho'_c(\mathbf{r}) \stackrel{\text{def}}{=} \frac{\max_{\Theta_1} \|\Psi_{\Theta_1}^\top \mathbf{r}\|_2}{\max_{\Theta_2} \|(\Phi_{\text{opt}})_{\Theta_2}^\top \mathbf{r}\|_2},$$

Note that $\rho'_c(\mathbf{r}) < 1$ is sufficient for $\rho_c(\mathbf{r}) < 1$, since for the other columns in $\Phi_{\Omega_1 \setminus \Theta_1}$, if it happens to have a larger absolute inner product with \mathbf{r} , we can switch it with a column in Φ_{Ω_2} to improve the maximum value obtained by Ω_2 in (4.2) since switching does not violate the condition $|\Omega_2 \cap \Lambda_{\text{opt}}| > |\Omega_1 \cap \Lambda_{\text{opt}}|$.

Next we show that the sufficient condition for $\rho(\mathbf{r}) < 1$ is also sufficient for $\rho'_c(\mathbf{r}) < 1$.

$$(4.10) \quad \begin{aligned} & \frac{\max_{\Theta_1} \|\Psi_{\Theta_1}^\top \mathbf{r}\|_2}{\max_{\Theta_2} \|(\Phi_{\text{opt}})_{\Theta_2}^\top \mathbf{r}\|_2} < 1 \\ \iff & \frac{\max_{\Theta_1} \sum_{\psi_j \in \Psi_{\Theta_1}} \|\psi_j^\top \mathbf{r}\|_2^2}{\max_{\Theta_2} \sum_{\varphi_l \in (\Phi_{\text{opt}})_{\Theta_2}} \|\varphi_l^\top \mathbf{r}\|_2^2} < 1. \end{aligned}$$

Now we sort in descending order the absolute inner products $|\langle \boldsymbol{\psi}_j, \mathbf{r} \rangle|$ and $|\langle \boldsymbol{\varphi}_l, \mathbf{r} \rangle|$, respectively. Let the index set $\Theta_1 = \{j_{(1)}, j_{(2)}, j_{(3)}, \dots\}$, and $\Theta_2 = \{l_{(1)}, l_{(2)}, l_{(3)}, \dots\}$ with subscript (i) indicating the i -th largest value. It is sufficient to show that $\rho'_c(\mathbf{r}) < 1$ as long as each of the following $\rho'_{(i)}(\mathbf{r}) < 1$, which is defined as

$$(4.11) \quad \rho'_{(i)}(\mathbf{r}) \stackrel{\text{def}}{=} \frac{|\langle \boldsymbol{\psi}_{j_{(i)}}, \mathbf{r} \rangle|}{|\langle \boldsymbol{\varphi}_{l_{(i)}}, \mathbf{r} \rangle|},$$

where $i = 1, \dots, |\Theta_1|$.

If $\rho(\mathbf{r}) < 1$ holds for the current iteration, then $\rho'_{(1)}(\mathbf{r}) < 1$ also holds, since $\rho(\mathbf{r}) = \rho'_{(1)}(\mathbf{r})$. After removing $j_{(1)}$ from Θ_1 and $l_{(1)}$ from Θ_2 , the the second largest becomes the largest, then we are facing the same problem again:

$$\rho'_{(2)}(\mathbf{r}) = \frac{\max_{\boldsymbol{\psi}} |\langle \boldsymbol{\psi}, \mathbf{r} \rangle|}{\max_{\boldsymbol{\varphi}} |\langle \boldsymbol{\varphi}, \mathbf{r} \rangle|},$$

where $\boldsymbol{\psi}$ ranges over columns in Ψ excluding $\boldsymbol{\psi}_{j_{(1)}}$, and $\boldsymbol{\varphi}$ ranges over columns in Φ_{opt} excluding $\boldsymbol{\varphi}_{j_{(1)}}$.

If condition $\mu_1(l) + \mu_1(n) < 1$ is satisfied, then $\rho'_{(2)}(\mathbf{r}) < 1$ also holds, and so on. Since $\rho'_{(i)}(\mathbf{r}) < 1$ holds for all i until exhausting all indices in Θ_1 and Θ_2 , and each term in the summation in (4.10) is nonnegative, then $\rho'_c(\mathbf{r}) < 1$ holds. Therefore $\mu_1(l) + \mu_1(n) < 1$ is also sufficient for $\rho_c(\mathbf{r}) < 1$.

Upper bound of $n + l$. It is trivial to show that $\mu_1(l) + \mu_1(n) \leq \mu(n + l)$. Therefore, it is necessary to find the upper bound of $n + l$.

Recall that n is the number of columns in X , and $l = \min(|\Pi|, k - 1)$, where Π denotes the index set for the columns in Φ_{opt} that have not been selected by the algorithm so far.

Before the first iteration, $n = k$, and $l = k - 1$, $n + l = 2k - 1$. If $\mu_1(l) + \mu_1(n) < 1$ holds, then $\rho_c(\mathbf{r}) < 1$ holds, so the greedy algorithm would select as many optimal columns as possible. As long as $|\Pi| \geq c$, it would select c optimal columns. Assume $k \geq c \geq 1$. After the first iteration, $n = k$ and $l = k - c$, therefore $n + l \leq 2k - 1$. In subsequent iterations, l decreases faster than n increases, thus $n + l$ is not increasing.

Therefore the upper bound for $n + l$ is

$$(4.12) \quad n + l \leq 2k - 1.$$

Combining Theorem 4.1 and upper bound (4.12), we have the following theorem:

THEOREM 4.5 (The strong exact recovery condition for BSR). *Suppose that μ is the coherence of the dictionary as defined in (4.6). A sufficient condition for BSR to recover a k -sparse signal within $\lceil k/c \rceil$ iterations is that*

$$(4.13) \quad \mu(2k - 1) < 1.$$

5. Approximation to General Signals. General signals may not have an exact sparse representation. In this case, the best we can obtain is its approximation. Suppose that for an arbitrary input signal \mathbf{y} , there exists a k -term optimal sparse approximation \mathbf{s}_{opt} , i.e., $\mathbf{y} = \mathbf{s}_{\text{opt}} + \boldsymbol{\varepsilon}$, and $\mathbf{s}_{\text{opt}} = \sum_{j \in \Lambda_{\text{opt}}} a_j \boldsymbol{\varphi}_j$, where $|\Lambda_{\text{opt}}| = k$. The difference between \mathbf{y} and its optimal approximation \mathbf{s}_{opt} is the irreducible error $\boldsymbol{\varepsilon}$. We can analyze the convergence property of the BSR algorithm from the perspectives of a sufficient condition under which the algorithm can find all optimal atoms within k iterations and the approximation error when the algorithm terminates. The approximation error will be measured by ℓ_2 norm.

5.1. Recovery Condition for General Signals. Suppose at the current iteration, the algorithm found a sparse representation $\mathbf{s} = \sum_{\boldsymbol{\varphi}_j \in \Phi} b_j \boldsymbol{\varphi}_j$, then the residual is $\mathbf{r} = \mathbf{y} - \mathbf{s}$. The algorithm can find at least one optimal column in Λ_{opt} in the next iteration if the greedy choice ratio $\rho(\mathbf{r}) < 1$.

$$\begin{aligned}
\rho(\mathbf{r}) &= \frac{\|\Psi^\top \mathbf{r}\|_\infty}{\|\Phi_{\text{opt}}^\top \mathbf{r}\|_\infty} \\
&= \frac{\|\Psi^\top (\mathbf{y} - \mathbf{s})\|_\infty}{\|\Phi_{\text{opt}}^\top (\mathbf{y} - \mathbf{s})\|_\infty} \\
&= \frac{\|\Psi^\top (\mathbf{y} - \mathbf{s}_{\text{opt}} + \mathbf{s}_{\text{opt}} - \mathbf{s})\|_\infty}{\|\Phi_{\text{opt}}^\top (\mathbf{y} - \mathbf{s}_{\text{opt}} + \mathbf{s}_{\text{opt}} - \mathbf{s})\|_\infty} \\
&\stackrel{(a)}{=} \frac{\|\Psi^\top (\mathbf{y} - \mathbf{s}_{\text{opt}} + \mathbf{s}_{\text{opt}} - \mathbf{s})\|_\infty}{\|\Phi_{\text{opt}}^\top (\mathbf{s}_{\text{opt}} - \mathbf{s})\|_\infty} \\
&\leq \frac{\|\Psi^\top (\mathbf{y} - \mathbf{s}_{\text{opt}})\|_\infty}{\|\Phi_{\text{opt}}^\top (\mathbf{s}_{\text{opt}} - \mathbf{s})\|_\infty} + \frac{\|\Psi^\top (\mathbf{s}_{\text{opt}} - \mathbf{s})\|_\infty}{\|\Phi_{\text{opt}}^\top (\mathbf{s}_{\text{opt}} - \mathbf{s})\|_\infty} \\
&= \rho_\varepsilon + \rho_t,
\end{aligned}$$

where (a) is due to that the columns in Φ_{opt} are orthogonal to the vector $\mathbf{y} - \mathbf{s}_{\text{opt}}$.

Therefore $\Phi_{\text{opt}}^\top (\mathbf{y} - \mathbf{s}_{\text{opt}})$ yields an all-zero vector.

The second term ρ_t is caused by the gap between what the algorithm has found so far and the optimal approximation. Obviously ρ_t is the same ρ we would get for a signal that has an exact sparse representation, i.e., when $\mathbf{y} = \mathbf{s}_{\text{opt}}$, therefore $\rho_t \leq \frac{\mu_1(n)}{1-\mu_1(l)}$ from (4.3) and (4.4).

The first term ρ_ε is caused by the irreducible error existing in the signal. ρ_ε can also be bounded.

$$\begin{aligned}
\rho_\varepsilon &= \frac{\|\Psi^\top (\mathbf{y} - \mathbf{s}_{\text{opt}})\|_\infty}{\|\Phi_{\text{opt}}^\top (\mathbf{s}_{\text{opt}} - \mathbf{s})\|_\infty} \\
&\stackrel{(a)}{\leq} \frac{\|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2}{\|\Phi_{\text{opt}}^\top (\mathbf{s}_{\text{opt}} - \mathbf{s})\|_\infty} \\
&\stackrel{(b)}{\leq} \frac{\sqrt{k} \|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2}{\|\Phi_{\text{opt}}^\top (\mathbf{s}_{\text{opt}} - \mathbf{s})\|_2} \\
&\stackrel{(c)}{\leq} \frac{\sqrt{k} \|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2}{\sigma_k(\Phi_{\text{opt}}) \|\mathbf{s}_{\text{opt}} - \mathbf{s}\|_2} \\
&\stackrel{(d)}{\leq} \frac{\sqrt{k} \|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2}{\sqrt{1 - \mu_1(k-1)} \|\mathbf{s}_{\text{opt}} - \mathbf{s}\|_2}
\end{aligned}$$

(a) is due to that $\|\Psi^\top (\mathbf{y} - \mathbf{s}_{\text{opt}})\|_\infty \leq \|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2$:

$$\begin{aligned}
\|\Psi^\top (\mathbf{y} - \mathbf{s}_{\text{opt}})\|_\infty &= \max_{\boldsymbol{\psi} \in \Psi} |\boldsymbol{\psi}^\top (\mathbf{y} - \mathbf{s}_{\text{opt}})| \\
&\leq \max_{\boldsymbol{\psi} \in \Psi} \|\boldsymbol{\psi}\|_2 \|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2 \\
&= \|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2
\end{aligned}$$

$\|\boldsymbol{\psi}\|_2 = 1$ since columns in Φ are normalized.

(b) is because for a $k \times 1$ vector \mathbf{v} , $\|\mathbf{v}\|_2 \leq \sqrt{k}\|\mathbf{v}\|_\infty$. Therefore $\|\Phi_{\text{opt}}^\top(\mathbf{s}_{\text{opt}} - \mathbf{s})\|_2 \leq \sqrt{k}\|\Phi_{\text{opt}}^\top(\mathbf{s}_{\text{opt}} - \mathbf{s})\|_\infty$.

(c) is due to the singular value definition. Φ_{opt} has k columns. The k -th singular value of Φ_{opt} is defined as

$$\sigma_k(\Phi_{\text{opt}}) = \inf_{\mathbf{u} \neq 0} \frac{\|\Phi_{\text{opt}}^\top \mathbf{u}\|_2}{\|\mathbf{u}\|_2},$$

and therefore,

$$(5.1) \quad \sigma_k(\Phi_{\text{opt}})\|\mathbf{s}_{\text{opt}} - \mathbf{s}\|_2 \leq \|\Phi_{\text{opt}}^\top(\mathbf{s}_{\text{opt}} - \mathbf{s})\|_2.$$

(d) is due to the relation of singular values to eigenvalues. Let matrix $Z = \Phi_{\text{opt}}^\top \Phi_{\text{opt}}$, then $\lambda_k(Z) = \sigma_k^2(\Phi_{\text{opt}})$. By the Gershgorin circle theorem, every eigenvalue of the square matrix Z lies within at least one of the Gershgorin discs, i.e.,

$$|\lambda - Z_{ii}| \leq \sum_{j \neq i} |Z_{ij}| = \sum_{j \neq i} |\langle \boldsymbol{\varphi}_i, \boldsymbol{\varphi}_j \rangle| \leq \mu_1(k-1),$$

and $Z_{ii} = 1$ since columns in Φ are normalized. Thus, $-\mu_1(k-1) \leq 1 - \lambda_k \leq \mu_1(k-1)$.

Therefore, $\sigma_k(\Phi_{\text{opt}}) \geq \sqrt{1 - \mu_1(k-1)}$. \square

Combining ρ_ε and ρ_t , we have

$$(5.2) \quad \rho(\mathbf{r}) \leq \frac{\sqrt{k}\|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2}{\sqrt{1 - \mu_1(k-1)}\|\mathbf{s}_{\text{opt}} - \mathbf{s}\|_2} + \frac{\mu_1(n)}{1 - \mu_1(l)}.$$

THEOREM 5.1 (General Recovery Condition of BSR). *The BSR algorithm can find all optimal atoms from Φ_{opt} within k iterations provided that the following condition holds for all iterations:*

$$(5.3) \quad \frac{\sqrt{k}\|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2}{\sqrt{1 - \mu_1(k-1)}\|\mathbf{s}_{\text{opt}} - \mathbf{s}\|_2} + \frac{\mu_1(n)}{1 - \mu_1(l)} < 1.$$

If the irreducible error $\|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2$ is nonzero, it imposes a more stringent condition on the dictionary Φ regarding the orthogonality between atoms, as it requires the

coherence μ to be very small to satisfy condition (5.3). Compared to signals that have exact sparse representations, the general signals are more difficult to recover. Noise works adversely for BSR the same way it does for OMP and OMP-SR.

5.2. Approximation Error of BSR. Let \mathbf{s}_κ represent the approximation solution found by the BSR algorithm, either after the fixed number of iterations, or after it breaks out from the **for** loop due to the residual $\|\mathbf{r}\|_2$ being too small. In the latter case, the residual is already bounded by δ given in the stopping criterion. We focus on the first case when the BSR algorithm has finished κ iterations, and ask what the upper bound for $\|\mathbf{y} - \mathbf{s}_\kappa\|_2$ will be. If the algorithm has found all k optimal atoms when it terminates, the approximation error is bounded by $\|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2$. It is only worth discussing when the algorithm has not found all optimal atoms after κ iterations.

We first consider a baseline solution that has only used the optimal atoms from Φ_{opt} so far, so that $\mathbf{s}_\kappa = \sum_{j \in \Lambda_{\text{opt}}} b_j \varphi_j$. From (5.3) we know that as long as the following condition holds, the algorithm will find at least one optimal atom in the next iteration:

$$\frac{\sqrt{k} \|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2}{\sqrt{1 - \mu_1(k-1)} \|\mathbf{s}_{\text{opt}} - \mathbf{s}\|_2} < \frac{1 - \mu_1(l) - \mu_1(n)}{1 - \mu_1(l)}$$

We need $\mu_1(l) + \mu_1(n) < 1$ to ensure that the right hand side of the inequality is positive.

The above inequality is equivalent to

$$\begin{aligned} \|\mathbf{s}_{\text{opt}} - \mathbf{s}\|_2 &> \frac{\sqrt{k}(1 - \mu_1(l)) \|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2}{\sqrt{1 - \mu_1(k-1)}(1 - \mu_1(l) - \mu_1(n))} \\ &\stackrel{(a)}{\geq} \frac{\sqrt{k(1 - \mu_1(k-1))}}{1 - \mu_1(l) - \mu_1(n)} \|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2 \\ &= h \|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2 \end{aligned}$$

$$\text{where } h = \frac{\sqrt{k(1 - \mu_1(k-1))}}{1 - \mu_1(l) - \mu_1(n)}.$$

(a) is due to that $l \leq k-1$, therefore $\mu_1(l) \leq \mu_1(k-1)$ based on the definition in (4.7), therefore $1 - \mu_1(l) \geq 1 - \mu_1(k-1)$.

If the algorithm fails to find an optimal atom in the next iteration, it is because

the above condition is broken, then we have

$$(5.4) \quad \|\mathbf{s}_{\text{opt}} - \mathbf{s}\|_2 \leq h\|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2.$$

Let $\mathbf{u} = \mathbf{y} - \mathbf{s}_{\text{opt}}$ and $\mathbf{v} = \mathbf{s}_{\text{opt}} - \mathbf{s}$. Then we have $\|\mathbf{v}\|_2 \leq h\|\mathbf{u}\|_2$ and $\mathbf{y} - \mathbf{s} = \mathbf{u} + \mathbf{v}$. In addition, \mathbf{u} and \mathbf{v} are orthogonal to each other since \mathbf{u} is the residual of projecting \mathbf{y} onto the column span of Φ_{opt} and \mathbf{v} is a vector in the column span of Φ_{opt} . From the Pythagorean Theorem that says if $\mathbf{u} \perp \mathbf{v}$, then $\|\mathbf{u} + \mathbf{v}\|_2 = \sqrt{\|\mathbf{u}\|_2^2 + \|\mathbf{v}\|_2^2}$. Thus,

$$(5.5) \quad \|\mathbf{y} - \mathbf{s}\|_2 \leq \sqrt{1 + h^2}\|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2.$$

This means if the algorithm fails to find an optimal atom in the next iteration, the current residual is upper bounded by $\sqrt{1 + h^2}\|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2$. The future iterations will not increase the residual due to the least square principle.

So far we have established the error bound for a baseline solution that only uses atoms from Φ_{opt} up to the current iteration. If BSR algorithm has used non-optimal columns in addition to those optimal atoms, the least square estimate will only produce smaller residual due to the least square principle, i.e.,

$$\|\mathbf{y} - \mathbf{s}_\kappa\|_2 \leq \|\mathbf{y} - \mathbf{s}\|_2 \leq \sqrt{1 + h^2}\|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2.$$

Therefore we can conclude that by the time the BSR algorithm has finished, the error bound is upper bounded by $\sqrt{1 + h^2}\|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2$.

THEOREM 5.2 (The Approximation Error of BSR). *Suppose that $\mu_1(l) + \mu_1(n) < 1$. Let $h = \frac{\sqrt{k(1-\mu_1(k-1))}}{1-\mu_1(l)-\mu_1(n)}$. The residual from the approximation solution \mathbf{s}_κ found by the BSR algorithm satisfies*

$$(5.6) \quad \|\mathbf{y} - \mathbf{s}_\kappa\|_2 \leq \sqrt{1 + h^2}\|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2$$

when the algorithm fails to find all optimal atoms, and

$$(5.7) \quad \|\mathbf{y} - \mathbf{s}_\kappa\|_2 \leq \|\mathbf{y} - \mathbf{s}_{\text{opt}}\|_2$$

when the algorithm succeeds in finding all optimal atoms.

6. Experiments. Data used in the experiments are posted at [github](#).




Fig. 1: The images used for experiment, (a) phantom, (b) transaxial CT, (c) trees, (d) letters, (e)–(h) MNIST dataset handwritten digits.

6.1. Sparse Signal Recovery. We first show sparse signal recovery performance when the signal has a sparse representation. The first experiment is on image data, where the non-zero elements constitute the content of an image, and exhibit continuity in the true signal \mathbf{x} . The images are shown in Figure 1. The second experiment is on signals defined on graph structures, where the non-zero elements are distributed among the nodes of a graph. We used synthetic data defined on a binary tree, and data that are collected from IEEE 118-bus power system and IEEE 1354-bus power system, where the true signal \mathbf{x} consists of the values of the state variables of a power system. Since the algorithms do not depend on the signal structure to find the non-zeros, they worked well with both types of data.

Table 1 and Table 2 show the performance of the proposed OMP-SR and BSR, and we report the number of iterations, the recovered optimal atoms, normalized MSE (NMSE), and running time in seconds. Image data are reported in Table 1, and graph

data are reported in Table 2.

If a k -sparse signal can be recovered by OMP within k iterations, it can certainly be recovered by BSR within k iterations. Those that cannot be recovered by OMP within k iterations are shown to take far less than k iterations and far less time by the BSR algorithm to fully recover. Since OMP-SR picks the same atoms as OMP does, we reported the result of OMP-SR in the same row as OMP and only reported its time (in blue text). It is observed that OMP-SR is faster than OMP, and BSR is faster than OMP and OMP-SR in every single test. The block size c in BSR is a hyper parameter searched from $\{2, 3, 4, 8\}$.

The third experiment is to show the relation between k and running time. Image data for the phantom and the MNIST handwritten digit '7' were used. We created different versions from the original image to have different image sizes d and different k/d ratios. Figure 2 shows how the running times and iterations of OMP, OMP-SR, and BSR increase as the number of non-zeros k increases. As k increases, BSR (blue curve) shows significant improvement in running time over OMP (red curve), while OMP-SR is in-between.

6.2. Sparse Approximation. The fourth experiment is for the general signal's sparse approximation. We added noise ε to the Phantom image, and reported the approximation error when the measurements are subject to increasing levels of noise. Table 3 shows that at each noise level, BSR found the k non-zeros with fewer iterations than OMP and significantly less running time.

7. Discussion and Future Work. OMP has the advantage of simplicity. A greedy algorithm such as OMP is easy to implement but difficult to analyze. This work offered significant performance improvement over the classical OMP with theoretical analysis for convergence and approximation error bound. In addition, the proposed extensions for OMP come from a principled approach. They work well when combined with other heuristic or ensemble approaches. One possible future work direction is to improve the greedy choice by leveraging the structure in the signal model.

The iterative approach of OMP (including ours) takes more iterations when k




Fig. 2: Running time (top) and iterations (bottom) used by the algorithms to recover k non-zeros in the signal. OMP and OMP-SR use the same number of iterations. The datasets used: (a),(c) phantom; (b),(d) MNIST dataset handwritten digit '7'.

increases, and the cost of orthogonal projection also increases. Our methods reduced the cost of orthogonal projection in each iteration, but the total cost still increases with iterations. The minimal ℓ_1 norm solution is the sparsest only when the signal is sparse enough [11]. Therefore another future work direction is to identify the specific measurement matrix property that drives sparsity during ℓ_1 norm minimization and use that to improve the greedy choice in an iterative procedure.

REFERENCES

- [1] A. S. BANDEIRA, E. DOBRIBAN, D. G. MIXON, AND W. F. SAWIN, *Certifying the restricted isometry property is hard*, IEEE Transactions on Information Theory, 59 (2013), pp. 3448–3450.
- [2] R. BARANIUK, M. DAVENPORT, R. DEVORE, AND M. WAKIN, *A simple proof of the restricted isometry property for random matrices*, Constructive Approximation, 28

Table 1: Image datasets. Reported NMSE and time in seconds. OMP-SR running time is highlighted in blue.

Data	k	method	ite	found	NMSE	time
MNIST(3) 392×784	126	OMP	126	110	0.0656	0.4077 (0.2977)
		OMP	142	126	<1e-11	0.5799 (0.3280)
		BSR	51	126	<1e-11	0.1298
MNIST(5) 392×784	162	OMP	162	99	0.7058	0.5902 (0.4204)
		OMP	784	162	<1e-11	18.0441 (12.993832)
		BSR	85	162	<1e-11	0.3926
MNIST(8) 392×784	174	OMP	174	92	0.8275	0.7703 (0.4934)
		OMP	546	174	<1e-11	11.0087 (6.5816)
		BSR	84	174	<1e-11	0.3855
MNIST(9) 392×784	130	OMP	130	125	0.0727	0.4453 (0.3190)
		OMP	135	130	<1e-11	0.5620 (0.3917)
		BSR	35	130	<1e-11	0.1111
Phantom 4512×9024	641	OMP	641	638	0.0278	89.0610 (70.8633)
		OMP	644	641	<1e-11	97.9924 (75.9530)
		BSR	81	641	<1e-11	9.1253
Transaxial CT 4225×8450	1089	OMP	1089	1064	0.0675	282.6071 (250.1557)
		OMP	1115	1089	<1e-11	302.0011 (263.0615)
		BSR	57	1089	<1e-11	14.0619
Trees 19200×38400	4670	OMP	4670	4652	0.00114	2391.0661 (702.4279)
		OMP	4688	4670	<1e-11	2571.1333 (754.8234)
		BSR	117	4670	<1e-11	20.0294
Letters 5712×11424	851	OMP	851	851	<1e-11	191.7733 (129.9197)
		BSR	107	851	<1e-11	16.4433

(2008), pp. 253–263, <https://doi.org/10.1007/s00365-007-9003-x>, <https://doi.org/10.1007/s00365-007-9003-x>.

- [3] E. J. CANDÉS, *The restricted isometry property and its implications for compressed sensing*, *Comptes rendus mathématique*, 346 (2008), pp. 589–592.
- [4] E. J. CANDÉS AND T. TAO, *Near-optimal signal recovery from random projections: Universal encoding strategies?*, *IEEE Transactions on Information Theory*, 52 (2006), pp. 5406–5425.
- [5] L.-H. CHANG AND J.-Y. WU, *An improved rip-based performance guarantee for sparse signal recovery via orthogonal matching pursuit*, *IEEE Transactions on Information Theory*, 60 (2014), pp. 5702–5715.
- [6] S. CHEN AND D. DONOHO, *Basis pursuit*, in *Proceedings of 1994 28th Asilomar Conference on*

Table 2: Synthetic data for signals defined on graph structures. Reported NMSE and time in seconds. OMP-SR running time is highlighted in blue.

Data	k	method	ite	found	NMSE	time
Binary Tree 256×512	70	OMP	70	70	<1e-11	0.1105 (0.0798)
		BSR	25	70	<1e-11	0.024294
118 Bus 59×118	14	OMP	14	14	<1e-11	0.0284 (0.0172)
		BSR	5	14	<1e-11	0.003876
118 Bus 59×118	100	OMP	100	86	0.8406	0.0706 (0.0582)
		OMP	118	100	<1e-11	0.0922 (0.0659)
		BSR	40	100	<1e-11	0.025842
1354 Bus 677×1354	270	OMP	270	215	0.2029	3.7723 (2.1686)
		OMP	336	270	<1e-11	5.4101 (3.4590)
		BSR	96	270	<1e-11	0.982119

Table 3: Results for the phantom image with increasing noise level $\|\epsilon\|_2$. Reported normalized approximation error $\frac{\|\mathbf{y}-\Phi\mathbf{x}\|_2}{\|\mathbf{y}\|_2}$, and running time in seconds. OMP-SR running time is highlighted in blue.

Noise	k	method	ite	found	$\frac{\ \mathbf{y}-\Phi\mathbf{x}\ _2}{\ \mathbf{y}\ _2}$	time
$\ \epsilon\ _2 = 0.1$	641	OMP	641	638	0.0231	88.7496 (70.3730)
		OMP	644	641	0.0001	94.6122 (72.1749)
		BSR	81	641	0.0001	9.1572
$\ \epsilon\ _2 = 50$	641	OMP	641	638	0.0777	87.1276 (70.6804)
		OMP	644	641	0.0727	95.4393 (71.5545)
		BSR	81	641	0.0720	9.7602
$\ \epsilon\ _2 = 100$	641	OMP	641	631	0.1470	88.9356 (72.0881)
		OMP	684	641	0.1337	165.5339 (138.7913)
		BSR	101	641	0.1287	13.8060
$\ \epsilon\ _2 = 150$	641	OMP	641	621	0.2687	89.2221 (70.3730)
		OMP	789	641	0.1671	134.5601 (101.7830)
		BSR	197	641	0.1671	25.4323

Signals, Systems and Computers, vol. 1, 1994, pp. 41–44.

[7] S. S. CHEN, D. L. DONOHO, AND M. A. SAUNDERS, *Atomic decomposition by basis pursuit*, SIAM Journal on Scientific Computing, 20 (1998), pp. 33–61.

[8] W. DAI AND O. MILENKOVIC, *Subspace pursuit for compressive sensing signal reconstruction*,

- IEEE Transactions on Information Theory, 55 (2009), pp. 2230–2249, <https://doi.org/10.1109/TIT.2009.2016006>.
- [9] I. DAUBECHIES, *Time-frequency localization operators: a geometric phase space approach*, IEEE Transactions on Information Theory, 34 (1988), pp. 605–612.
- [10] S. DIRKSEN, G. LECUÁ, AND H. RAUHUT, *On the gap between restricted isometry properties and sparse recovery conditions*, IEEE Transactions on Information Theory, 64 (2018), pp. 5478–5487.
- [11] D. L. DONOHO, *For most large underdetermined systems of linear equations the minimal ℓ_1 -norm solution is also the sparsest solution*, Communications on Pure and Applied Mathematics, 59 (2006), pp. 797–829.
- [12] D. L. DONOHO AND M. ELAD, *Optimally sparse representation in general (nonorthogonal) dictionaries via ℓ^1 minimization*, Proceedings of the National Academy of Sciences, 100 (2003), pp. 2197–2202.
- [13] D. L. DONOHO, Y. TSAIG, I. DRORI, AND J. STARCK, *Sparse solution of underdetermined systems of linear equations by stagewise orthogonal matching pursuit*, IEEE Transactions on Information Theory, 58 (2012), pp. 1094–1121, <https://doi.org/10.1109/TIT.2011.2173241>.
- [14] H. GE AND W. CHEN, *Recovery of signals by a weighted $\ell_2\ell_1$ minimization under arbitrary prior support information*, Signal Processing, 148 (2018), pp. 288–302.
- [15] S. KWON, J. WANG, AND B. SHIM, *Multipath matching pursuit*, IEEE Transactions on Information Theory, 60 (2014), pp. 2986–3001, <https://doi.org/10.1109/TIT.2014.2310482>.
- [16] S. MALLAT AND Z. ZHANG, *Matching pursuits with time-frequency dictionaries*, IEEE Transactions on Signal Processing, 41 (1993), pp. 3397–3415.
- [17] D. NEEDELL AND J. A. TROPP, *Cosamp: Iterative signal recovery from incomplete and inaccurate samples*, Applied and computational harmonic analysis, 26 (2009), pp. 301–321.
- [18] D. NEEDELL AND R. VERSHYNIN, *Uniform uncertainty principle and signal recovery via regularized orthogonal matching pursuit*, Foundations of Computational Mathematics, 9 (2009), pp. 317–334.
- [19] Y. PATI, R. REZAIFAR, AND P. KRISHNAPRASAD, *Orthogonal matching pursuit: recursive function approximation with applications to wavelet decomposition*, in Proceedings of 27th Asilomar Conference on Signals, Systems and Computers, vol. 1, 1993, pp. 40–44.
- [20] A. M. TILLMANN AND M. E. PFETSCH, *The computational complexity of the restricted isometry property, the nullspace property, and related concepts in compressed sensing*, IEEE Transactions on Information Theory, 60 (2013), pp. 1248–1259.
- [21] J. A. TROPP, *Greed is good: Algorithmic results for sparse approximation*, IEEE Transactions on Information theory, 50 (2004), pp. 2231–2242.
- [22] J. A. TROPP AND A. C. GILBERT, *Signal recovery from random measurements via orthogonal matching pursuit*, IEEE Transactions on information theory, 53 (2007), pp. 4655–4666.
- [23] P. YIN, Y. LOU, Q. HE, AND J. XIN, *Minimization of ℓ_{1-2} for compressed sensing*, SIAM

Appendix: OMP Algorithm. The OMP algorithm from [19] is listed here for reference

Algorithm 7.1 OMP [19]

Input: $\Phi \in \mathbb{R}^{N \times d}$, $\mathbf{y} \in \mathbb{R}^N$, κ
Initialization: $\mathbf{r}^0 = \mathbf{y}$, $\Gamma = J^0 = \phi$, $\mathcal{J} = \{1, \dots, d\}$
for $t = 1$ **to** κ **do**
 Choose $\lambda^t = \arg \max_{j \in \mathcal{J} \setminus \Gamma} |\langle \varphi_j, \mathbf{r}^{t-1} \rangle|$
 Update index set $\Gamma = \Gamma \cup \{\lambda^t\}$
 Estimate $\hat{\mathbf{s}}^t = \arg \min_{\mathbf{s}} \|\mathbf{y} - \Phi \mathbf{s}\|_2^2$ by setting the l -th entry $s_l = 0$ for $l \notin \Gamma$
 Update residual $\mathbf{r}^t = \mathbf{y} - \Phi \hat{\mathbf{s}}^t$
end for
Return $\{\hat{\mathbf{s}}^t\}_{t=1}^{\kappa}$
